

Support for the HP ProCurve BX Transceivers:

J9099B ProCurve 100-BX-D SFP-LC Transceiver

J9100B ProCurve 100-BX-U SFP-LC Transceiver

J9142B ProCurve 1000-BX-D SFP-LC Mini-GBIC

J9143B ProCurve 1000-BX-U SFP-LC Mini-GBIC

Best practice tip: After inserting a transceiver into a switch, the Mode LED will come on for two seconds while the transceiver is initialized. Do not remove the transceiver until the Mode LED has turned off. For the Switch 2600 and 2800 Series: After inserting a transceiver into a 2600 or 2800 switch, the "M" LED will come on to indicate that the mini-GBIC slot is active. Wait at least two seconds after the "M" LED comes on if you need to remove the transceiver.

Product	Minimum Software Required for 100-BX	Minimum Software Required for 1000-BX	Support Notes
Switch 1400 Series J9077A J9078A	N/A	Any software version	For use in the SFP ports of the J9078A Switch 1400-24G. (The J9077A Switch 1400-8G does not have SFP ports.) 100-BX is not supported.
Switch 1700 Series J9079A J9080A	N/A	VB.02.00	For use in the SFP ports of the J9080A Switch 1700-24. (The J9079A Switch 1700-8 does not have SFP ports.) 100-BX is not supported.
Switch 1800 Series J9028A/B J9029A	N/A	PB.03.00	For use in the SFP ports of the J9028A/B Switch 1800-24G. (The J9029A Switch 1800-8G does not have SFP ports.) 100-BX is not supported.
1810 Series Switches J9449A J9450A	Any software version	N/A	For use in the SFP ports of the J9450A 1810G-24 Switch. (The J9449A 1810G-8 Switch does not have SFP ports.) 1000-BX is not supported.
Switch 2510-24 J9019A/B	Q.11.16	Q.11.16	
Switch 2510-48 J9020A	U.11.10	U.11.10	
Switch 2510G Series J9279A J9280A	Y.11.03	Y.11.03	
2520 Series Switches J9137A J9138A J9298A J9299A	Any software version	Any software version	

Product	Minimum Software Required for 100-BX	Minimum Software Required for 1000-BX	Support Notes
Switch 2600 Series J4899A/B/C J4900A/B/C J8164A J8165A J8762A	N/A	H.10.72	100-BX is not supported.
Switch 2610 Series J9085A J9086A J9087A J9088A J9089A	R.11.22	R.11.22	
Switch 2800 Series J4903A J4904A	I.10.69	I.10.69	
Switch 2810 Series J9021A J9022A	N.11.14	N.11.14	
Switch 2900 Series J9049A J9050A	T.13.45	T.13.45	
2910al Series Switches J9145A J9146A J9147A J9148A	Any software version	Any software version	
Switch 3400cl Series J4905A J4906A	N/A	N/A	BX is not supported in these products
3500 Series Switches J9470A J9471A J9472A J9473A	K.14.31	K.14.31	
Switch 3500yl Series J8692A J8693A	K.13.45	K.13.45	
Switch 4100gl Series J4865A J4887A	N/A	N/A	BX is not supported in these products
Switch 4200vl Series J8770A J8771A J8772A/B J8773A	L.11.16	L.11.16	100-BX is supported in <u>only</u> the J9033A 20-Port Gig-T + 4-Port SFP Module. 100-BX is not supported in the J8776A 4-Port Mini-GBIC Module.
Switch 5300xl Series J4819A J4850A	N/A	E.11.08	100-BX is not supported.

Product	Minimum Software Required for 100-BX	Minimum Software Required for 1000-BX	Support Notes
Switch 5400zl Series J8697A J8698A	For J8705A and J8706A modules: K.13.45 For the J9308A module: K.14.34	For J8705A and J8706A modules: K.13.45 For the J9308A module: K.14.34	For use in the J8705A Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the J8706A Switch zl 24-Port Mini-GBIC Module, and the J9308A 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module.
Switch 6108 J4902A	N/A	N/A	BX is not supported in this product.
6120 Series Blade Switches 498358-B21 516733-B21	N/A	N/A	BX is not supported in these product.s
Switch 6200yl-24G-mGBIC J8992A	K.13.45	K.13.45	
6600 Series Switches J9263A J9264A J9265A J9451A J9452A	For J9263A, J9264A: K.14.03 For J9451A: K.14.24	For J9263A, J9264A: K.14.03 For J9451A: K.14.24	For use in the SFP ports of the J9263A 6600-24G Switch, the J9264A 6600-24G-4XG Switch, and the J9451A 6600-48G Switch. (The J9265A 6600-24XG Switch and J9452A 6600-48G-4XG Switch do not have SFP ports.)
Switch 8100fl Series J8727A J8728A	N/A	N/A	BX is not supported in these product.s
Switch 8200zl Series J8715A/B J9475A	For J8705A and J8706A modules: K.13.45 For the J9308A module: K.14.34	For J8705A and J8706A modules: K.13.45 For the J9308A module: K.14.34	For use in the J8705A Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the J8706A Switch zl 24-Port Mini-GBIC Module, and the J9308A 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module.
Switch 9300m Series J4138A J4139A J4874A	N/A	N/A	BX is not supported in these product.s
Switch 9408sl J8680A	N/A	N/A	BX is not supported in this product.

Software Updates Are *Free!*

Hewlett-Packard provides free software updates on the HP ProCurve Web site for your switch. To access the software updates, go to the HP ProCurve Web site at www.hp.com/go/procurve, then click on **Software downloads** to go to the “HP ProCurve Networking software releases” page. Under **Download the latest software** click on **Switches** to go to the page that has the free download for your switch.

Register for Automatic Notification of Updates. From the “HP ProCurve Networking software downloads” page, you can also register yourself to automatically receive email notice of new updates for your managed HP ProCurve networking products.

To determine whether you have the latest software, you can compare the software version that is available on the Web site with the version that is currently installed on your switch.

© Copyright 2009 Hewlett-Packard Company, L.P.
The information contained herein is subject to
change without notice.

October 2009

