

ProCurve Networking 10-GbE Transceiver Support Matrix

ProCurve Switch Series	Product Name	Product Number	Genuine ProCurve X2					Genuine ProCurve Optical Media Converter (OMC) for CX4 (J8439A)	Genuine ProCurve XENPAK 10GBASE-SR, LR, ER (J8175A, J8173A, J8176A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4 (J8440A) (J8440B)			
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
2900	Switch 2900-24G	J9049A	all software versions	T.13.18 and later	all software versions	all software versions	all software versions	all software versions, OMC for fixed CX4 ports only	--
	Switch 2900-48G	J9050A							
3400cl	Switch 3400cl-24G	J4905A	--	--	--	--	--	--	--
	Switch 3400cl-48G	J4906A							
	Switch cl 10-GbE CX4 Copper Module	J8434A	--	--	--	--	--		
	Switch cl 10-GbE Media Flex Module	J8435A	M.08.54 and later	--	M.08.75 and later	M.08.54 and later	M.10.06 and later	M.08.54 and later, OMC for J8434A & J8440A/B	
3500yl	Switch 3500yl-24G-PWR	J8692A	--	--	--	--	--	--	--
	Switch 3500yl-48G-PWR	J8693A							
	Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module	J8694A	all software versions	K.13.20 and later	all software versions	all software versions	K.11.17 and later	all software versions, OMC for fixed CX4 ports only	
4200vl	Switch vl 1-Port 10-GbE X2 Module	J8766A	L.11.08 and later	L.11.11 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	--
5300xl	Switch xl 1-Port 10-GbE X2 Module	J8988A	E.11.02 and later	--	E.11.02 and later	E.11.02 and later	E.11.02 and later	E.11.02 and later	--
5400zl	Switch zl 4-Port 10-GbE X2 Module	J8707A	all software versions	K.13.20 and later	all software versions	all software versions	K.11.17 and later	K.11.33 and later, OMC for J8708A & J8440A/B	--
	Switch zl 4-Port 10-GbE CX4 Module	J8708A	--	--	--	--	--		
6200yl	Switch 6200yl-24G-mGBIC	J8992A	--	--	--	--	--	K.11.33 and later, OMC for fixed CX4 ports only	--
	Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module	J8694A	K.11.33 and later	K.13.20 and later	K.11.33 and later	K.11.33 and later	K.11.33 and later		
6400cl	Switch 6400cl (CX4)	J8433A	--	--	--	--	--	M.08.62 and later, OMC for J8433A & J8440A/B	--
	Switch 6410cl (X2)	J8474A	M.08.62 and later	--	M.08.75 and later	M.08.62 and later	M.08.102 and later		
	Switch cl 10-GbE CX4 Copper Module	J8434A	--	--	--	--	--		
	Switch cl 10-GbE Media Flex Module	J8435A	M.08.62 and later	--	M.08.75 and later	M.08.62 and later	M.08.102 and later		
8100fl	Switch fl 1-Port 10-GbE X2 Interface Module	J8736A	CY.02.03.0005 and later	--	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later, OMC for J8440A/B	--
	Switch fl 2-Port 10-GbE X2 Interface Module	J8737A	CY.02.05.0001 and later	--	CY.02.05.0001 and later	CY.02.05.0001 and later	CY.02.05.0001 and later	CY.02.05.0001 and later, OMC for J8440A/B	
8200zl	Switch zl 4-Port 10-GbE X2 Module	J8707A	all software versions	K.13.20 and later	all software versions	all software versions	all software versions	all software versions, OMC for J8708A & J8440A/B	--
	Switch zl 4-Port 10-GbE CX4 Module	J8708A	--	--	--	--	--		
9300m	9300 2-Port 10-GbE Module	J8174A	--	--	--	--	--	--	07.6.04 and later
9408sl	9400sl 4-Port 10-GbE Module	J8682A	--	--	--	--	--	--	all software versions