

HP ProCurve Networking 10-GbE Transceiver Support Matrix

HP ProCurve Switch Series	Product Name	Product Number	Genuine HP ProCurve X2 Transceivers					Genuine HP ProCurve Optical Media Converter (OMC) for CX4 (J8439A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4		
			Supported with This Software	Supported with This Software	Supported with This Software	(J8440A) Supported with This Software	(J8440B) Supported with This Software	
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	all software versions	T.13.18 and later	all software versions	all software versions	all software versions	all software versions, OMC for fixed CX4 ports only
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE CX4 al Module	J9145A J9147A J9146A J9148A J9149A	-- -- -- --	-- -- -- --	-- -- -- --	-- -- -- --	-- -- -- --	-- -- -- -- all software versions
3400cl	Switch 3400cl-24G Switch 3400cl-48G Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J4905A J4906A J8434A J8435A	-- -- -- M.08.54 and later	-- -- -- --	-- -- -- M.08.75 and later	-- -- -- M.08.54 and later	-- -- -- M.10.06 and later	-- -- M.08.54 and later, OMC for J8434A & J8440A/B
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module	J8692A J8693A J8694A	-- -- all software versions	-- -- K.13.20 and later	-- -- all software versions	-- -- all software versions	-- -- K.11.17 and later	-- -- all software versions, OMC for fixed CX4 ports only
4200vl	Switch vl 1-Port 10-GbE X2 Module	J8766A	L.11.08 and later	L.11.11 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later
5300xl	Switch xl 1-Port 10-GbE X2 Module	J8988A	E.11.02 and later	--	E.11.02 and later	E.11.02 and later	E.11.02 and later	E.11.02 and later
5400zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions --	K.13.20 and later --	all software versions --	all software versions --	K.11.17 and later --	K.11.33 and later, OMC for J8708A & J8440A/B
6200yl	Switch 6200yl-24G-mGBIC Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module	J8992A J8694A	-- K.11.33 and later	-- K.13.20 and later	-- K.11.33 and later	-- K.11.33 and later	-- K.11.33 and later	-- K.11.33 and later, OMC for fixed CX4 ports only
6400cl	Switch 6400cl (CX4) Switch 6410cl (X2) Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J8433A J8474A J8434A J8435A	-- M.08.62 and later -- M.08.62 and later	-- -- -- --	-- M.08.75 and later -- M.08.75 and later	-- M.08.62 and later -- M.08.62 and later	-- M.08.102 and later -- M.08.102 and later	M.08.62 and later, OMC for J8433A & J8440A/B M.08.62 and later, OMC for J8434A & J8440A/B
8100fl	Switch fl 1-Port 10-GbE X2 Interface Module Switch fl 2-Port 10-GbE X2 Interface Module	J8736A J8737A	CY.02.03.0005 and later CY.02.05.0001 and later	-- --	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later, OMC for J8440A/B CY.02.05.0001 and later, OMC for J8440A/B
8200zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions --	K.13.20 and later --	all software versions --	all software versions --	all software versions --	all software versions, OMC for J8708A & J8440A/B

HP ProCurve Networking 10-GbE Transceiver Support Matrix (cont'd)

			Genuine HP ProCurve SFP+ Transceivers and Cables			
HP ProCurve Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM (J9150A, J9151A, J9152A)	10-GbE SFP+ Direct Attach Cables 1m, 3m, 7m (J9281A, J9283A, J9285A) (J9281B, J9283B, J9285B)		10-GbE XFP-SFP+ Direct Attach Cables 1m, 3m, 5m (J9300A, J9301A, J9302A)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2910al	2910al-24G Switch	J9145A				
	2910al-48G Switch	J9147A	--	--	--	--
	2910al-24G-PoE+ Switch	J9146A				
	2910al-48G-PoE+ Switch	J9148A				
	2-Port 10-GbE SFP+ al Module	J9008A	all software versions	all software versions	W.14.28 and later	W.14.28 and later
5400zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.14.39 and later	K.14.39 and later	K.14.39 and later	K.14.39 and later
6120	6120G/XG Blade Switch	498358-B21	--	--	--	all software versions
	6120XG Blade Switch	516733-B21	all software versions	all software versions	all software versions	--
6600	6600-24G-4XG Switch	J9264A	K.14.03 and later	K.14.03 and later	K.14.32 and later	K.14.32 and later
	6600-24XG Switch	J9265A				
	6600-48G-4XG Switch	J9452A	K.14.24 and later	K.14.24 and later	K.14.32 and later	
8200zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.14.39 and later	K.14.39 and later	K.14.39 and later	K.14.39 and later

			Genuine HP ProCurve XENPAK Transceivers
HP ProCurve Switch Series	Product Name	Product Number	10GBASE-SR, LR, ER (J8175A, J8173A, J8176A)
			Supported with This Software
9300m	9300 2-Port 10-GbE Module	J8174A	07.6.04 and later
9408sl	9400sl 4-Port 10-GbE Module	J8682A	all software versions