

Support for the J9054B 100-FX SFP-LC Transceiver

Product	Minimum Software Required	Support Notes
Switch 1400 Series J9077A J9078A	N/A	100-FX is not supported in these products.
Switch 1700 Series J9079A J9080A	N/A	100-FX is not supported in these products.
Switch 1800 Series J9028A/B J9029A	N/A	100-FX is not supported in these products.
1810 Series Switches J9449A J9450A	Any software version	For use in the SFP ports of the J9450A 1810G-24 Switch. (The J9449A 1810G-8 Switch does not have SFP ports.)
Switch 2510-24 J9019A/B	Q.10.04	
Switch 2510-48 J9020A	Any software version	
Switch 2510G Series J9279A J9280A	Any software version	
2520 Series Switches J9137A J9138A J9298A J9299A	Any software version	
Switch 2600 Series J4899A/B/C J4900A/B/C J8164A J8165A J8762A	N/A	100-FX is not supported in these products.
Switch 2610 Series J9085A J9086A J9087A J9088A J9089A	Any software version	
Switch 2800 Series J4903A J4904A	I.10.30	
Switch 2810 Series J9021A J9022A	N.10.07	
Switch 2900 Series J9049A J9050A	T.12.01	

Product	Minimum Software Required	Support Notes
2910al Series Switches J9145A J9146A J9147A J9148A	Any software version	
Switch 3400cl Series J4905A J4906A	N/A	100-FX is not supported in these products.
3500 Series Switches J9470A J9471A J9472A J9473A	K.14.31	
Switch 3500yl Series J8692A J8693A	K.12.01	
Switch 4100gl Series J4865A J4887A	N/A	100-FX is not supported in these products.
Switch 4200vl Series J8770A J8771A J8772A/B J8773A	L.10.24	Supported: J9033A Switch vl 20-Port Gig-T + 4-Port SFP Module. Not supported: J8776A Switch vl 4-Port Mini-GBIC Module.
Switch 5300xl Series J4819A J4850A	N/A	100-FX is not supported in these products.
Switch 5400zl Series J8697A J8698A	For J8705A and J8706A modules: K.12.01 For the J9308A module: K.14.34	For use in the J8705A Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the J8706A Switch zl 24-Port Mini-GBIC Module, and the J9308A 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module.
Switch 6108 J4902A	N/A	100-FX is not supported in this product.
6120 Series Blade Switches 498358-B21 516733-B21	N/A	100-FX is not supported in these products.
Switch 6200yl-24G-mGBIC J8992A	K.12.01	For use in all 24 ports of the J8992A Switch 6200yl-24G-mGBIC.
6600 Series Switches J9263A J9264A J9265A J9451A J9452A	For J9263A, J9264A: K.14.03 For J9451A: K.14.24	For use in the SFP ports of the J9263A 6600-24G Switch, the J9264A 6600-24G-4XG Switch, and the J9451A 6600-48G Switch. (The J9265A 6600-24XG Switch and J9452A 6600-48G-4XG Switch do not have SFP ports.)
Switch 8100fl Series J8727A J8728A	N/A	100-FX is not supported in these products.

Product	Minimum Software Required	Support Notes
Switch 8200zl Series J8715A/B J9475A	For J8705A and J8706A modules: Any software version For the J9308A module: K.14.34	For use in the J8705A Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the J8706A Switch zl 24-Port Mini-GBIC Module, and the J9308A 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module.
Switch 9300m Series J4138A J4139A J4874A	N/A	100-FX is not supported in these products.
Switch 9408sl J8680A	N/A	100-FX is not supported in this product.

Software Updates Are Free!

Hewlett-Packard provides free software updates on the HP ProCurve Web site for your switch. To access the software updates, go to the HP ProCurve Web site at www.hp.com/go/procurve, then click on **Software downloads** to go to the "HP ProCurve Networking software releases" page. Under **Download the latest software** click on **Switches** to go to the page that has the free download for your switch.

Register for Automatic Notification of Updates. From the "HP ProCurve Networking software downloads" page, you can also register yourself to automatically receive email notice of new updates for your managed HP ProCurve networking products.

To determine whether you have the latest software, you can compare the software version that is available on the Web site with the version that is currently installed on your switch.

© Copyright 2009 Hewlett-Packard Company, L.P.
The information contained herein is subject to
change without notice.

October 2009

