

ProCurve Networking Mini-GBIC and SFP Support Matrix

			Genuine ProCurve Mini-GBICs and SFPs				
ProCurve Switch Series	Product Name	Product Number	"A" versions	"B" versions		"C" versions	
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B)	1000Base-T ¹ (J8177B)	100-FX (J9054B)	Gigabit-SX, LX, LH (J4858C, J4859C, J4860C)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400-24G	J9078A	all software versions ²	all software versions ²	(not supported)	(not supported)	all software versions ²
1700	Switch 1700-24	J9080A	all software versions ²	all software versions ²	(not supported)	(not supported)	VB.01.09 and later ²
1800	Switch 1800-24G	J9028A/B	all software versions ²	all software versions ²	(not supported)	(not supported)	PB.02.09 and later ²
2510	Switch 2510-24	J9019A/B	(not supported)	all software versions	(not supported)	Q.10.04 and later	all software versions
	Switch 2510-48	J9020A	(not supported)	all software versions	all software versions	all software versions	all software versions
	Switch 2510G-24	J9279A	(not supported)	all software versions	(not supported)	all software versions	all software versions
	Switch 2510G-48	J9280A	(not supported)	all software versions	(not supported)	all software versions	all software versions
2600	Switch 2626	J4899A/B/C	all software versions	all software versions	(not supported)	(not supported)	H.08.98 and later
	Switch 2650	J4900A/B/C					
	Switch 2626-PWR	J8164A					
	Switch 2650-PWR	J8165A					
	Switch 2600-8-PWR	J8762A					
2610	Switch 2610-24	J9085A	(not supported)	all software versions	all software versions	all software versions	all software versions
	Switch 2610-48	J9088A					
	Switch 2610-24-PWR	J9087A					
	Switch 2610-48-PWR	J9089A					
	Switch 2610-24/12PWR	J9086A					
2800	Switch 2824	J4903A	all software versions	all software versions	(not supported)	i.10.30 and later	i.08.103 and later
	Switch 2848	J4904A					
2810	Switch 2810-24G	J9021A	(not supported)	all software versions	(not supported)	N.10.07 and later	all software versions
	Switch 2810-48G	J9022A					
2900	Switch 2900-24G	J9049A	(not supported)	all software versions	(not supported)	T.12.01 and later	all software versions
	Switch 2900-48G	J9050A					
3400cl	Switch 3400cl-24G	J4905A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	Switch 3400cl-48G	J4906A					
3500yl	Switch 3500yl-24G-PWR	J8692A	(not supported)	all software versions	(not supported)	K.12.01 and later	all software versions
	Switch 3500yl-48G-PWR	J8693A					
4100gl	Switch gl 6-Port Mini-GBIC Module	J4893A	all software versions	all software versions	G.07.69 and later	(not supported)	G.07.103 and later
	Switch gl 20-Port 10/100/1000 Module	J4908A					

Genuine ProCurve Mini-GBICs and SFPs (continued)

ProCurve Switch Series	Product Name	Product Number	"A" versions	"B" versions	"C" versions		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B)	1000Base-T ¹ (J8177B)	100-FX (J9054B)	Gigabit-SX, LX, LH (J4858C, J4859C, J4860C)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
4200vl	Switch vl 4-Port Mini-GBIC Module	J8766A	(not supported)	all software versions	all software versions	(not supported)	all software versions
	Switch vl 20-Port Gig-T + 4-Port SFP Module	J9033A				L.10.24 and later	
5300xl	Switch xl 4-Port Mini-GBIC Module	J4878A/B	all software versions	all software versions	E.09.22 and later	(not supported)	E.10.36 and later
	Switch xl 16-Port 10/100/1000 Module	J4907A			(not supported)		
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	all software versions	all software versions	K.12.01 and later	all software versions
	Switch zl 24-Port Mini-GBIC Module	J8706A					
6108	Switch 6108	J4902A	all software versions	all software versions	(not supported)	(not supported)	H.07.88 and later
6200yl	Switch 6200yl-24G-mGBIC	J8992A	(not supported)	all software versions	all software versions	K.12.01 and later	all software versions
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	(not supported)	all software versions	CY.01.02.0050 and later	(not supported)	all software versions
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	all software versions	all software versions	all software versions	all software versions
	Switch zl 24-Port Mini-GBIC Module	J8706A					
9300m	EP 8-Port Mini-GBIC Redundant Management Module	J4885A	all software versions	all software versions	07.8.00a and later ³	(not supported)	all software versions
	EP 16-Port Mini-GBIC Module	J4894A					
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	all software versions	02.1.00c and later	(not supported)	all software versions

ProCurve Networking Mini-GBIC and SFP Support Information

- ProCurve products and accessories offer a lifetime warranty, unsurpassed in the marketplace.
- ProCurve Networking stands behind our products because we build them to precise specifications and thoroughly test them.
- ProCurve mini-GBICs and SFPs are specified and tested as rigorously as the devices in which they are used.
- Non-ProCurve mini-GBICs and SFPs are of unknown quality and therefore cannot be supported with our lifetime warranty.

Footnotes

¹ The J8177B 1000Base-T mini-GBIC is not supported in dual-personality ports.

² Gigabit-LH-LC Mini-GBICs (J4860A, J4860B, J4860C) are not supported in this product.

³ For the 9300m series, the J8177B 1000Base-T mini-GBIC is supported only in EP modules, with software version 07.8.00a and later.

⁴ 3rd party products from non-ProCurve vendors are not supported and will not function.

⁵ Non-genuine ProCurve "B version" and "C version" mini-GBICs are not supported and will not function.

⁶ Supported: Qualified for operation in ProCurve switches and for warranty support from ProCurve Networking.

⁷ Might function: The ProCurve switch attempts to enable this non-ProCurve mini-GBIC.



Non-ProCurve Mini-GBIC and SFP Support

ProCurve Switch Series	Software Versions	Genuine 3rd Party "A versions" from ProCurve Vendors ⁴		Non-Genuine ProCurve SX, LX, LH "A versions" ⁵	
		Supported? ⁶	Might Function? ⁷	Supported?	Might Function?
1400-24G (J9078A)	all software versions	no	yes	no	yes
1700-24 (J9080A)	all software versions	no	yes	no	yes
1800-24G (J9028A/B)	all software versions	no	yes	no	yes
2510 (J9019A/B, J9020A, J9279A, J9280A)	all software versions	no	no	no	no
2600 'A' (J4899A, J4900A)	H.07.02 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600-PWR (J8164A, J8165A)	H.07.41 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600 'B', 2600 'C' (J4899B/C, J4900B/C)	all software versions	no	yes	no	no
2600-8-PWR (J8762A)	all software versions	no	yes	no	no
2610	all software versions	no	no	no	no
2810	all software versions	no	no	no	no
2824, 2848 (serial # < SG505xxxxx)	i.07.31 - i.08.80	no	yes	no	yes
	i.08.81 - i.08.97	no	yes	no	no
	i.08.98 and later	no	yes	no	yes
2824, 2848 (serial # >= SG505xxxxx)	i.07.31 - i.08.50	no	yes	no	yes
	i.08.51 - i.08.102	no	yes	no	no
	i.08.103 and later	no	yes	no	yes
2900	all software versions	no	no	no	no
3400cl	all software versions	no	yes	no	no
3500yl	all software versions	no	no	no	no
4100gl	all software versions	no	yes	no	yes
4200vl	all software versions	no	no	no	no
5300xl	E.05.04 - E.10.04	no	yes	no	yes
	E.10.05 - E.10.35	no	yes	no	no
	E.10.36 and later	no	yes	no	yes
5400zl	all software versions	no	no	no	no
6108	all software versions	no	yes	no	yes
6200yl	all software versions	no	no	no	no
8100fl	all software versions	no	no	no	no
8200zl	all software versions	no	no	no	no
9300m, 9408sl	all software versions	no	yes	no	yes

