

HP ProCurve Networking Mini-GBIC and SFP Support Matrix

			Genuine HP ProCurve Mini-GBICs and SFPs				
			Gigabit "B" and "C" versions				
HP ProCurve Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T ¹ (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400-24G	J9078A	all software versions	all software versions	(not supported)	(not supported)	all software versions
1700	Switch 1700-24	J9080A	all software versions	VB.01.09 and later	(not supported)	(not supported)	VB.02.00 and later
1800	Switch 1800-24G	J9028A/B	all software versions	PB.02.09 and later	(not supported)	(not supported)	PB.03.00 and later
1810	1810G-24 Switch	J9450A	all software versions	all software versions	(not supported)	(not supported)	(not supported)
2510	Switch 2510-24	J9019A/B	all software versions	all software versions	(not supported)	(not supported)	Q.11.16 and later
	Switch 2510-48	J9020A			all software versions	all software versions	U.11.10 and later
	Switch 2510G-24	J9279A			(not supported)	(not supported)	Y.11.03 and later
	Switch 2510G-48	J9280A					
2520	2520-8-PoE Switch	J9137A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	2520-24-PoE Switch	J9138A					
	2520G-8-PoE Switch	J9298A					
	2520G-24-PoE Switch	J9299A					
2600	Switch 2626	J4899A/B/C	all software versions	H.08.98 and later	(not supported)	(not supported)	H.10.72 and later
	Switch 2650	J4900A/B/C					
	Switch 2626-PWR	J8164A					
	Switch 2650-PWR	J8165A					
	Switch 2600-8-PWR	J8762A					
2610	Switch 2610-24	J9085A	all software versions	all software versions	all software versions	all software versions	R.11.22 and later
	Switch 2610-48	J9088A					
	Switch 2610-24-PWR	J9087A					
	Switch 2610-48-PWR	J9089A					
	Switch 2610-24/12PWR	J9086A					
2800	Switch 2824	J4903A	all software versions	i.08.103 and later	(not supported)	(not supported)	i.10.69 and later
	Switch 2848	J4904A					
2810	Switch 2810-24G	J9021A	all software versions	all software versions	(not supported)	(not supported)	N.11.14 and later
	Switch 2810-48G	J9022A					
2900	Switch 2900-24G	J9049A	all software versions	all software versions	(not supported)	(not supported)	T.13.45 and later
	Switch 2900-48G	J9050A					
2910al	2910al-24G Switch	J9145A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	2910al-48G Switch	J9147A					
	2910al-24G-PoE+ Switch	J9146A					
	2910al-48G-PoE+ Switch	J9148A					
3400cl	Switch 3400cl-24G	J4905A	all software versions	all software versions	(not supported)	(not supported)	(not supported)
	Switch 3400cl-48G	J4906A					

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

Gigabit "B" and "C" versions

HP ProCurve Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T ¹ (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
3500	3500-24 Switch 3500-48 Switch 3500-24-PoE Switch 3500-48-PoE Switch	J9470A J9472A J9471A J9473A	K.14.31 and later	K.14.31 and later	(not supported)	(not supported)	K.14.31 and later
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR	J8692A J8693A	all software versions	all software versions	(not supported)	(not supported)	K.13.45 and later
4100gl	Switch gl 6-Port Mini-GBIC Module Switch gl 20-Port 10/100/1000 Module	J4893A J4908A	all software versions	G.07.103 and later	G.07.69 and later	G.07.69 and later	(not supported)
4200vl	Switch vl 4-Port Mini-GBIC Module Switch vl 20-Port Gig-T + 4-Port SFP Module	J8776A J9033A	all software versions	all software versions	all software versions	all software versions	L.11.16 and later
5300xl	Switch xl 4-Port Mini-GBIC Module Switch xl 16-Port 10/100/1000 Module	J4878A/B J4907A	all software versions	E.10.36 and later	E.09.22 and later (not supported)	E.09.22 and later (not supported)	E.11.08 and later
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module Switch zl 24-Port Mini-GBIC Module 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J8705A J8706A J9308A	all software versions K.14.34 and later	all software versions K.14.34 and later	all software versions K.14.34 and later	all software versions K.14.34 and later	K.13.45 and later K.14.34 and later
6108	Switch 6108	J4902A	all software versions	H.07.88 and later	(not supported)	(not supported)	(not supported)
6120	6120G/XG Blade Switch 6120XG Blade Switch	498358-B21 516733-B21	SX, LX: all versions LH: not supported	SX, LX: all versions LH: not supported	all software versions	all software versions	(not supported)
6200yl	Switch 6200yl-24G-mGBIC	J8992A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later
6600	6600-24G Switch 6600-24G-4XG Switch 6600-48G Switch	J9263A J9264A J9451A	K.14.03 and later K.14.24 and later	K.14.03 and later K.14.24 and later	(not supported)	(not supported)	K.14.03 and later K.14.24 and later
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	all software versions	all software versions	CY.01.02.0050 and later	CY.01.02.0050 and later	(not supported)
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module Switch zl 24-Port Mini-GBIC Module 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J8705A J8706A J9308A	all software versions K.14.34 and later	all software versions K.14.34 and later	all software versions K.14.34 and later	all software versions K.14.34 and later	K.13.45 and later K.14.34 and later
9300m	EP 8-Port Mini-GBIC Redundant Management Module EP 16-Port Mini-GBIC Module	J4885A J4894A	all software versions	all software versions	07.8.00a and later ²	(not supported)	(not supported)
9408sl	9408sl 40-Port Mini-GBIC Module	J8684A	all software versions	all software versions	02.1.00c and later	(not supported)	(not supported)

HP ProCurve Networking Mini-GBIC and SFP Support Information

- HP ProCurve products and accessories offer a lifetime warranty, unsurpassed in the marketplace.
- HP ProCurve Networking stands behind our products because we build them to precise specifications and thoroughly test them.
- HP ProCurve mini-GBICs and SFPs are specified and tested as rigorously as the devices in which they are used.
- Non-ProCurve mini-GBICs and SFPs are of unknown quality and therefore cannot be supported with our lifetime warranty.

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

HP ProCurve Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs	
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400-24G	J9078A	all software versions	(not supported)	(not supported)
1700	Switch 1700-24	J9080A	all software versions	(not supported)	(not supported)
1800	Switch 1800-24G	J9028A/B	all software versions	(not supported)	(not supported)
1810	1810G-24 Switch	J9450A	all software versions	all software versions	all software versions
2510	Switch 2510-24	J9019A/B	(not supported)	Q.10.04 and later	Q.11.16 and later
	Switch 2510-48	J9020A		all software versions	U.11.10 and later
	Switch 2510G-24	J9279A		all software versions	Y.11.03 and later
	Switch 2510G-48	J9280A			
2520	2520-8-PoE Switch	J9137A	(not supported)	all software versions	all software versions
	2520-24-PoE Switch	J9138A			
	2520G-8-PoE Switch	J9298A			
	2520G-24-PoE Switch	J9299A			
2600	Switch 2626	J4899A/B/C	all software versions	(not supported)	(not supported)
	Switch 2650	J4900A/B/C			
	Switch 2626-PWR	J8164A			
	Switch 2650-PWR	J8165A			
2600-8-PWR	Switch 2600-8-PWR	J8762A			
2610	Switch 2610-24	J9085A	(not supported)	all software versions	R.11.22 and later
	Switch 2610-48	J9088A			
	Switch 2610-24-PWR	J9087A			
	Switch 2610-48-PWR	J9089A			
	Switch 2610-24/12PWR	J9086A			
2800	Switch 2824	J4903A	all software versions	i.10.30 and later	i.10.69 and later
	Switch 2848	J4904A			
2810	Switch 2810-24G	J9021A	(not supported)	N.10.07 and later	N.11.14 and later
	Switch 2810-48G	J9022A			
2900	Switch 2900-24G	J9049A	(not supported)	T.12.01 and later	T.13.45 and later
	Switch 2900-48G	J9050A			
2910al	2910al-24G Switch	J9145A	(not supported)	all software versions	all software versions
	2910al-48G Switch	J9147A			
	2910al-24G-PoE+ Switch	J9146A			
	2910al-48G-PoE+ Switch	J9148A			
3400cl	Switch 3400cl-24G	J4905A	all software versions	(not supported)	(not supported)
	Switch 3400cl-48G	J4906A			

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

HP ProCurve Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs	
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software
3500	3500-24 Switch	J9470A	(not supported)	K.14.31 and later	K.14.31 and later
	3500-48 Switch	J9472A			
	3500-24-PoE Switch	J9471A			
	3500-48-PoE Switch	J9473A			
3500yl	Switch 3500yl-24G-PWR	J8692A	(not supported)	K.12.01 and later	K.13.45 and later
	Switch 3500yl-48G-PWR	J8693A			
4100gl	Switch gl 6-Port Mini-GBIC Module	J4893A	all software versions	(not supported)	(not supported)
	Switch gl 20-Port 10/100/1000 Module	J4908A			
4200vl	Switch vl 4-Port Mini-GBIC Module	J8776A	(not supported)	(not supported)	(not supported)
	Switch vl 20-Port Gig-T + 4-Port SFP Module	J9033A		L.10.24 and later	L.11.16 and later
5300xl	Switch xl 4-Port Mini-GBIC Module	J4878A/B	all software versions	(not supported)	(not supported)
	Switch xl 16-Port 10/100/1000 Module	J4907A			
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	K.12.01 and later	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A			
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A			
6108	Switch 6108	J4902A	all software versions	(not supported)	(not supported)
6120	6120G/XG Blade Switch	498358-B21	(not supported)	(not supported)	(not supported)
	6120XG Blade Switch	516733-B21			
6200yl	Switch 6200yl-24G-mGBIC	J8992A	(not supported)	K.12.01 and later	K.13.45 and later
6600	6600-24G Switch	J9263A	(not supported)	K.14.03 and later	K.14.03 and later
	6600-24G-4XG Switch	J9264A			
	6600-48G Switch	J9451A			
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	(not supported)	(not supported)	(not supported)
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	all software versions	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A			
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A			
9300m	EP 8-Port Mini-GBIC Redundant Management Module	J4885A	all software versions	(not supported)	(not supported)
	EP 16-Port Mini-GBIC Module	J4894A			
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	(not supported)	(not supported)

Footnotes

¹ The J8177B/C 1000BASE-T mini-GBIC is not supported in dual-personality ports.

² For the 9300m, the J8177B 1000BASE-T mini-GBIC is supported only in EP modules.

³ 3rd party products from non-ProCurve vendors are not supported and will not function.

⁴ Non-genuine ProCurve "B version" and "C version" mini-GBICs are not supported and will not function.

⁵ Supported: Qualified for operation in HP ProCurve switches and warranty support from HP ProCurve Networking.

⁶ Might function: The HP ProCurve switch attempts to enable this non-ProCurve mini-GBIC.

Non-ProCurve Mini-GBIC and SFP Support

HP ProCurve Switch Series	Software Versions	Genuine 3rd Party "A versions" from ProCurve Vendors ³		Non-Genuine ProCurve SX, LX, LH "A versions" ⁴	
		Supported? ⁵	Might Function? ⁶	Supported?	Might Function?
1400-24G (J9078A)	all software versions	no	yes	no	yes
1700-24 (J9080A)	all software versions	no	yes	no	yes
1800-24G (J9028A/B), 1810G-24 (J9450A)	all software versions	no	yes	no	yes
2510, 2520	all software versions	no	no	no	no
2600 'A' (J4899A, J4900A)	H.07.02 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600-PWR (J8164A, J8165A)	H.07.41 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600 'B', 2600 'C' (J4899B/C, J4900B/C)	all software versions	no	yes	no	no
2600-8-PWR (J8762A)	all software versions	no	yes	no	no
2610	all software versions	no	no	no	no
2810	all software versions	no	no	no	no
2824, 2848 (serial # < SG505xxxx)	i.07.31 - i.08.80	no	yes	no	yes
	i.08.81 - i.08.97	no	yes	no	no
	i.08.98 and later	no	yes	no	yes
2824, 2848 (serial # >= SG505xxxx)	i.07.31 - i.08.50	no	yes	no	yes
	i.08.51 - i.08.102	no	yes	no	no
	i.08.103 and later	no	yes	no	yes
2900, 2910a1	all software versions	no	no	no	no
3400cl	all software versions	no	yes	no	no
3500, 3500yl	all software versions	no	no	no	no
4100gl	all software versions	no	yes	no	yes
4200vl	all software versions	no	no	no	no
5300xl	E.05.04 - E.10.04	no	yes	no	yes
	E.10.05 - E.10.35	no	yes	no	no
	E.10.36 and later	no	yes	no	yes
5400zl	all software versions	no	no	no	no
6108	all software versions	no	yes	no	yes
6120, 6200yl, 6600	all software versions	no	no	no	no
8100fl	all software versions	no	no	no	no
8200zl	all software versions	no	no	no	no
9300m, 9408sl	all software versions	no	yes	no	yes